

WIRELESS PHONE-INTERFACE DEVICE

FIELD OF THE INVENTION

5 The present invention relates generally to security systems and components that operate in security systems. More particularly, the present invention relates to a wireless phone-interface device within a security system.

COPYRIGHT NOTICE/PERMISSION

10 A portion of the disclosure of this patent document contains material which is subject to copyright protection. The copyright owner has no objection to the facsimile reproduction by anyone of the patent document or the patent disclosure as it appears in the Patent and Trademark Office patent file or records, but otherwise reserves all copyright rights whatsoever. The following notice applies to the software and data as described below and in the drawings hereto: Copyright ©
15 Interactive Technologies, Incorporated, 2000. All Rights Reserved.

BACKGROUND OF THE INVENTION

20 In a security system, a control panel receives signals from security devices distributed throughout a monitoring area, such as a home, business, or warehouse, to monitor various sensor events. The security devices placed throughout the monitoring area might include door/window sensors, glass-break sensors, motion detectors, temperature sensors, smoke sensors, and the like. When a sensor event is sensed, such as a door/window open, movement, smoke, or fire, the sensor sends a sensor event to a control panel, which based on its installation programming and
25 current user setting determines the appropriate system response. In some cases, the control panel will start an entry delay period, in others, e.g. a fire, the control panel may sound an immediate alarm. A system response such as entry delay, can lead to further system actions, such as an alarm and a report of the system state to an off-

premises monitoring station, such as a monitoring company central station, fire station, or police station.

Security systems typical delay reporting of at least one of the sensor events (e.g. door open) to the monitoring station for some period of time sufficient to allow
5 a valid user time to disarm the reporting prior to the expiration of an entry delay timer and therefore prevent an alarm report to the monitoring station. This delay in reporting is called "entry delay," as opposed to "dialer delay," which is an additional time delay between when the control panel determines that the monitoring station should be notified and when the dialer actually reports the alarm via a telephone call
10 to the monitoring station.

Current self-contained security systems – with the user interface, dialer, siren, and processing functions integrated into a single unit – are vulnerable to attack because the entry delay time period gives an unauthorized intruder time to break open and disable the control panel before the control panel has reported the sensor
15 event via the dialer. Also, for ease of installation and consumer convenience, the user interface is typically located near the normal premise entry point, which makes it easy for the intruder to find the dialer since they are integrated together. Further, the low-level siren sounds during the entry delay period, which are intended to prompt the valid user to disarm the system, but also aids the intruder in finding the
20 self-contained security system including the critical dialer..

Current hardwired and wireless self-contained security systems typically run a wire from the control panel to the telephone demarcation point (the "head in" point) prior to all telephone sets in the facility. This distance can be quite long, which makes installation expensive. This wire to the demarcation point is necessary
25 because the security system must be able to seize the telephone line, so that the security system can report a sensor event to the monitoring station even if a

premise's telephone-set receiver is off-hook. Line seizure means that the control panel disconnects all other premise telephones.

Another disadvantage of current security systems is the expense in isolating the telephone line from alternating current (AC) used by the control panel.

5 Telephone companies, government regulations, and/or safety standards require electrical isolation in order to provide product reliability and ensure customer safety. This is commonly accomplished with an isolation transformer, a transient surge-protection device, and/or other expensive components installed in the control panel, which electrically isolate the AC power from the telephone line and ensure safety.

10 Thus, a significant need exists for methods and systems that reduce the costs of obtaining security protection and that provide better protection against unauthorized intruders.

SUMMARY OF THE INVENTION

15 The present invention provides solutions to the above-described shortcomings in conventional approaches, as well as other advantages apparent from the description below. The present invention is a method, system, apparatus, and program product related to a wireless phone-interface device in a security system.

20 In one aspect, a phone-interface device determines whether a problem has occurred at a control panel by determining whether a signal from a control panel has been received, and when a signal has not been received within a period of time, the phone-interface device transmits an error message to a monitoring station.

In another aspect, the control panel determines whether a problem has occurred at the phone-interface device by determining whether a signal from the

phone-interface device has been received, and when a signal has not been received within a period of time, the control panel transmits an error message to a user.

5 In another aspect, the phone-interface device contains memory to buffer data transferred between the control panel and a monitoring station. In this way, a high-speed connection between the phone-interface and the monitoring station can be accommodated while using a lower-speed connection between the phone-interface device and the control panel.

10
11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
31
32
33
34
35
36
37
38
39
40
41
42
43
44
45
46
47
48
49
50
51
52
53
54
55
56
57
58
59
60
61
62
63
64
65
66
67
68
69
70
71
72
73
74
75
76
77
78
79
80
81
82
83
84
85
86
87
88
89
90
91
92
93
94
95
96
97
98
99
100
101
102
103
104
105
106
107
108
109
110
111
112
113
114
115
116
117
118
119
120
121
122
123
124
125
126
127
128
129
130
131
132
133
134
135
136
137
138
139
140
141
142
143
144
145
146
147
148
149
150
151
152
153
154
155
156
157
158
159
160
161
162
163
164
165
166
167
168
169
170
171
172
173
174
175
176
177
178
179
180
181
182
183
184
185
186
187
188
189
190
191
192
193
194
195
196
197
198
199
200
201
202
203
204
205
206
207
208
209
210
211
212
213
214
215
216
217
218
219
220
221
222
223
224
225
226
227
228
229
230
231
232
233
234
235
236
237
238
239
240
241
242
243
244
245
246
247
248
249
250
251
252
253
254
255
256
257
258
259
260
261
262
263
264
265
266
267
268
269
270
271
272
273
274
275
276
277
278
279
280
281
282
283
284
285
286
287
288
289
290
291
292
293
294
295
296
297
298
299
300
301
302
303
304
305
306
307
308
309
310
311
312
313
314
315
316
317
318
319
320
321
322
323
324
325
326
327
328
329
330
331
332
333
334
335
336
337
338
339
340
341
342
343
344
345
346
347
348
349
350
351
352
353
354
355
356
357
358
359
360
361
362
363
364
365
366
367
368
369
370
371
372
373
374
375
376
377
378
379
380
381
382
383
384
385
386
387
388
389
390
391
392
393
394
395
396
397
398
399
400
401
402
403
404
405
406
407
408
409
410
411
412
413
414
415
416
417
418
419
420
421
422
423
424
425
426
427
428
429
430
431
432
433
434
435
436
437
438
439
440
441
442
443
444
445
446
447
448
449
450
451
452
453
454
455
456
457
458
459
460
461
462
463
464
465
466
467
468
469
470
471
472
473
474
475
476
477
478
479
480
481
482
483
484
485
486
487
488
489
490
491
492
493
494
495
496
497
498
499
500
501
502
503
504
505
506
507
508
509
510
511
512
513
514
515
516
517
518
519
520
521
522
523
524
525
526
527
528
529
530
531
532
533
534
535
536
537
538
539
540
541
542
543
544
545
546
547
548
549
550
551
552
553
554
555
556
557
558
559
560
561
562
563
564
565
566
567
568
569
570
571
572
573
574
575
576
577
578
579
580
581
582
583
584
585
586
587
588
589
590
591
592
593
594
595
596
597
598
599
600
601
602
603
604
605
606
607
608
609
610
611
612
613
614
615
616
617
618
619
620
621
622
623
624
625
626
627
628
629
630
631
632
633
634
635
636
637
638
639
640
641
642
643
644
645
646
647
648
649
650
651
652
653
654
655
656
657
658
659
660
661
662
663
664
665
666
667
668
669
670
671
672
673
674
675
676
677
678
679
680
681
682
683
684
685
686
687
688
689
690
691
692
693
694
695
696
697
698
699
700
701
702
703
704
705
706
707
708
709
710
711
712
713
714
715
716
717
718
719
720
721
722
723
724
725
726
727
728
729
730
731
732
733
734
735
736
737
738
739
740
741
742
743
744
745
746
747
748
749
750
751
752
753
754
755
756
757
758
759
760
761
762
763
764
765
766
767
768
769
770
771
772
773
774
775
776
777
778
779
780
781
782
783
784
785
786
787
788
789
790
791
792
793
794
795
796
797
798
799
800
801
802
803
804
805
806
807
808
809
810
811
812
813
814
815
816
817
818
819
820
821
822
823
824
825
826
827
828
829
830
831
832
833
834
835
836
837
838
839
840
841
842
843
844
845
846
847
848
849
850
851
852
853
854
855
856
857
858
859
860
861
862
863
864
865
866
867
868
869
870
871
872
873
874
875
876
877
878
879
880
881
882
883
884
885
886
887
888
889
890
891
892
893
894
895
896
897
898
899
900
901
902
903
904
905
906
907
908
909
910
911
912
913
914
915
916
917
918
919
920
921
922
923
924
925
926
927
928
929
930
931
932
933
934
935
936
937
938
939
940
941
942
943
944
945
946
947
948
949
950
951
952
953
954
955
956
957
958
959
960
961
962
963
964
965
966
967
968
969
970
971
972
973
974
975
976
977
978
979
980
981
982
983
984
985
986
987
988
989
990
991
992
993
994
995
996
997
998
999
1000
1001
1002
1003
1004
1005
1006
1007
1008
1009
1010
1011
1012
1013
1014
1015
1016
1017
1018
1019
1020
1021
1022
1023
1024
1025
1026
1027
1028
1029
1030
1031
1032
1033
1034
1035
1036
1037
1038
1039
1040
1041
1042
1043
1044
1045
1046
1047
1048
1049
1050
1051
1052
1053
1054
1055
1056
1057
1058
1059
1060
1061
1062
1063
1064
1065
1066
1067
1068
1069
1070
1071
1072
1073
1074
1075
1076
1077
1078
1079
1080
1081
1082
1083
1084
1085
1086
1087
1088
1089
1090
1091
1092
1093
1094
1095
1096
1097
1098
1099
1100
1101
1102
1103
1104
1105
1106
1107
1108
1109
1110
1111
1112
1113
1114
1115
1116
1117
1118
1119
1120
1121
1122
1123
1124
1125
1126
1127
1128
1129
1130
1131
1132
1133
1134
1135
1136
1137
1138
1139
1140
1141
1142
1143
1144
1145
1146
1147
1148
1149
1150
1151
1152
1153
1154
1155
1156
1157
1158
1159
1160
1161
1162
1163
1164
1165
1166
1167
1168
1169
1170
1171
1172
1173
1174
1175
1176
1177
1178
1179
1180
1181
1182
1183
1184
1185
1186
1187
1188
1189
1190
1191
1192
1193
1194
1195
1196
1197
1198
1199
1200
1201
1202
1203
1204
1205
1206
1207
1208
1209
1210
1211
1212
1213
1214
1215
1216
1217
1218
1219
1220
1221
1222
1223
1224
1225
1226
1227
1228
1229
1230
1231
1232
1233
1234
1235
1236
1237
1238
1239
1240
1241
1242
1243
1244
1245
1246
1247
1248
1249
1250
1251
1252
1253
1254
1255
1256
1257
1258
1259
1260
1261
1262
1263
1264
1265
1266
1267
1268
1269
1270
1271
1272
1273
1274
1275
1276
1277
1278
1279
1280
1281
1282
1283
1284
1285
1286
1287
1288
1289
1290
1291
1292
1293
1294
1295
1296
1297
1298
1299
1300
1301
1302
1303
1304
1305
1306
1307
1308
1309
1310
1311
1312
1313
1314
1315
1316
1317
1318
1319
1320
1321
1322
1323
1324
1325
1326
1327
1328
1329
1330
1331
1332
1333
1334
1335
1336
1337
1338
1339
1340
1341
1342
1343
1344
1345
1346
1347
1348
1349
1350
1351
1352
1353
1354
1355
1356
1357
1358
1359
1360
1361
1362
1363
1364
1365
1366
1367
1368
1369
1370
1371
1372
1373
1374
1375
1376
1377
1378
1379
1380
1381
1382
1383
1384
1385
1386
1387
1388
1389
1390
1391
1392
1393
1394
1395
1396
1397
1398
1399
1400
1401
1402
1403
1404
1405
1406
1407
1408
1409
1410
1411
1412
1413
1414
1415
1416
1417
1418
1419
1420
1421
1422
1423
1424
1425
1426
1427
1428
1429
1430
1431
1432
1433
1434
1435
1436
1437
1438
1439
1440
1441
1442
1443
1444
1445
1446
1447
1448
1449
1450
1451
1452
1453
1454
1455
1456
1457
1458
1459
1460
1461
1462
1463
1464
1465
1466
1467
1468
1469
1470
1471
1472
1473
1474
1475
1476
1477
1478
1479
1480
1481
1482
1483
1484
1485
1486
1487
1488
1489
1490
1491
1492
1493
1494
1495
1496
1497
1498
1499
1500
1501
1502
1503
1504
1505
1506
1507
1508
1509
1510
1511
1512
1513
1514
1515
1516
1517
1518
1519
1520
1521
1522
1523
1524
1525
1526
1527
1528
1529
1530
1531
1532
1533
1534
1535
1536
1537
1538
1539
1540
1541
1542
1543
1544
1545
1546
1547
1548
1549
1550
1551
1552
1553
1554
1555
1556
1557
1558
1559
1560
1561
1562
1563
1564
1565
1566
1567
1568
1569
1570
1571
1572
1573
1574
1575
1576
1577
1578
1579
1580
1581
1582
1583
1584
1585
1586
1587
1588
1589
1590
1591
1592
1593
1594
1595
1596
1597
1598
1599
1600
1601
1602
1603
1604
1605
1606
1607
1608
1609
1610
1611
1612
1613
1614
1615
1616
1617
1618
1619
1620
1621
1622
1623
1624
1625
1626
1627
1628
1629
1630
1631
1632
1633
1634
1635
1636
1637
1638
1639
1640
1641
1642
1643
1644
1645
1646
1647
1648
1649
1650
1651
1652
1653
1654
1655
1656
1657
1658
1659
1660
1661
1662
1663
1664
1665
1666
1667
1668
1669
1670
1671
1672
1673
1674
1675
1676
1677
1678
1679
1680
1681
1682
1683
1684
1685
1686
1687
1688
1689
1690
1691
1692
1693
1694
1695
1696
1697
1698
1699
1700
1701
1702
1703
1704
1705
1706
1707
1708
1709
1710
1711
1712
1713
1714
1715
1716
1717
1718
1719
1720
1721
1722
1723
1724
1725
1726
1727
1728
1729
1730
1731
1732
1733
1734
1735
1736
1737
1738
1739
1740
1741
1742
1743
1744
1745
1746
1747
1748
1749
1750
1751
1752
1753
1754
1755
1756
1757
1758
1759
1760
1761
1762
1763
1764
1765
1766
1767
1768
1769
1770
1771
1772
1773
1774
1775
1776
1777
1778
1779
1780
1781
1782
1783
1784
1785
1786
1787
1788
1789
1790
1791
1792
1793
1794
1795
1796
1797
1798
1799
1800
1801
1802
1803
1804
1805
1806
1807
1808
1809
1810
1811
1812
1813
1814
1815
1816
1817
1818
1819
1820
1821
1822
1823
1824
1825
1826
1827
1828
1829
1830
1831
1832
1833
1834
1835
1836
1837
1838
1839
1840
1841
1842
1843
1844
1845
1846
1847
1848
1849
1850
1851
1852
1853
1854
1855
1856
1857
1858
1859
1860
1861
1862
1863
1864
1865
1866
1867
1868
1869
1870
1871
1872
1873
1874
1875
1876
1877
1878
1879
1880
1881
1882
1883
1884
1885
1886
1887
1888
1889
1890
1891
1892
1893
1894
1895
1896
1897
1898
1899
1900
1901
1902
1903
1904
1905
1906
1907
1908
1909
1910
1911
1912
1913
1914
1915
1916
1917
1918
1919
1920
1921
1922
1923
1924
1925
1926
1927
1928
1929
1930
1931
1932
1933
1934
1935
1936
1937
1938
1939
1940
1941
1942
1943
1944
1945
1946
1947
1948
1949
1950
1951
1952
1953
1954
1955
1956
1957
1958
1959
1960
1961
1962
1963
1964
1965
1966
1967
1968
1969
1970
1971
1972
1973
1974
1975
1976
1977
1978
1979
1980
1981
1982
1983
1984
1985
1986
1987
1988
1989
1990
1991
1992
1993
1994
1995
1996
1997
1998
1999
2000
2001
2002
2003
2004
2005
2006
2007
2008
2009
2010
2011
2012
2013
2014
2015
2016
2017
2018
2019
2020
2021
2022
2023
2024
2025
2026
2027
2028
2029
2030
2031
2032
2033
2034
2035
2036
2037
2038
2039
2040
2041
2042
2043
2044
2045
2046
2047
2048
2049
2050
2051
2052
2053
2054
2055
2056
2057
2058
2059
2060
2061
2062
2063
2064
2065
2066
2067
2068
2069
2070
2071
2072
2073
2074
2075
2076
2077
2078
2079
2080
2081
2082
2083
2084
2085
2086
2087
2088
2089
2090
2091
2092
2093
2094
2095
2096
2097
2098
2099
2100
2101
2102
2103
2104
2105
2106
2107
2108
2109
2110
2111
2112
2113
2114
2115
2116
2117
2118
2119
2120
2121
2122
2123
2124
2125
2126
2127
2128
2129
2130
2131
2132
2133
2134
2135
2136
2137
2138
2139
2140
2141
2142
2143
2144
2145
2146
2147
2148
2149
2150
2151
2152
2153
2154
2155
2156
2157
2158
2159
2160
2161
2162
2163
2164
2165
2166
2167
2168
2169
2170
2171
2172
2173
2174
2175
2176
2177
2178
2179
2180
2181
2182
2183
2184
2185
2186
2187
2188
2189
2190
2191
2192
2193
2194
2195
2196
2197
2198
2199
2200
2201
2202
2203
2204
2205
2206
2207
2208
2209
2210
2211
2212
2213
2214

BRIEF DESCRIPTION OF THE DRAWINGS

Fig. 1 illustrates a pictorial example of a facility with a security system, according to an embodiment of the invention.

5 Fig. 2 illustrates a block diagram showing additional detail for selected elements of the security system.

Fig. 3 illustrates a flowchart that describes a method at a control panel for receiving and processing events, according to an embodiment of the invention.

10 Fig. 4 illustrates a flowchart that describes a method at a phone-interface device for receiving and processing events, according to an embodiment of the invention.

Fig. 5 illustrates a flowchart that describes a method at a phone-interface device for transferring data between a control panel and a monitoring station, according to an embodiment of the invention.

15 Fig. 6A illustrates a flowchart that describes a method at a phone-interface device for charging an energy storage device from a phone line, according to an embodiment of the invention.

Fig. 6B illustrates a flowchart that describes a method at a phone-interface device for charging an energy storage device from a phone line, according to an embodiment of the invention.

20 Fig. 7A illustrates a flowchart that describes a method at a control panel for sending a status message to a phone-interface device, according to an embodiment of the invention.

Fig. 7B illustrates a flowchart that describes a method at a phone-interface device for detecting when a control panel has an error condition.

Fig. 8A illustrates a flowchart that describes a method at a phone-interface device for sending a status message to a control panel, according to an embodiment of the invention.

5 Fig. 8B illustrates a flowchart that describes a method at a control panel for detecting when a phone-interface device has an error condition.

Fig. 9 illustrates a flowchart that describes a method at a phone-interface device for receiving telephone calls, according to an embodiment of the invention.

Fig. 10 illustrates a flowchart of the RF main routine of the phone-interface device.

10

Fig. 11 is a flowchart of the Provisional Alarm routine of the phone-interface device.

15

Fig. 12 illustrates a flowchart of the Clear Provisional Alarm routine of the phone-interface device.

20

Fig. 13 illustrates a flowchart of the Delayed Alarm and Start Delayed Alarms routines of the phone-interface device.

Fig. 14 illustrates a flowchart of the Immediate Alarm and Start Immediate Alarms routines of the phone-interface device.

25

Fig. 15 illustrates a flowchart of the Cancel Alarm routine of the phone-interface device.

Fig. 16 illustrates a flowchart of the Expire Provisional Timer routine of the phone-interface device.

5 Fig. 17 illustrates a flowchart of the Expire Dialer Timer routine of the phone-interface device.

Fig. 18 illustrates a flowchart of the Set Armed State routine of the phone-interface device.

10 Fig. 19 illustrates a flowchart of the Set Disarmed State routine of the phone-interface device.

Fig. 20 illustrates a flowchart fo the Phone Main routine of the phone-interface device controller.

15

DETAILED DESCRIPTION OF THE INVENTION

20 In the following detailed description of exemplary embodiments of the invention, reference is made to the accompanying drawings (where like numbers represent like elements) that form a part hereof, and in which is shown by way of illustration specific exemplary embodiments in which the invention may be practiced. These embodiments are described in sufficient detail to enable those skilled in the art to practice the invention, but other embodiments may be utilized and logical, mechanical, electrical, and other changes may be made without departing from the scope of the present invention. The following detailed description is, 25 therefore, not to be taken in a limiting sense, and the scope of the present invention is defined only by the appended claims.

Fig. 1 depicts a pictorial example of a facility with a security system, according to an embodiment of the invention. Facility 100 includes security system 112. In one embodiment facility 100 is a house, but in other embodiments facility 100 can be a business, warehouse, or any other type of structure needing security.

5 For protection against intruder tampering, control panel 114 ordinarily is locked in a durable housing and placed in a remote location within facility 100, unless it is a self-contained panel. Control panel 114 optionally activates siren 125 and transmits system conditions to phone-interface device 140. Phone-interface device 140 uses communications link 141 to transmit system conditions to an unillustrated off-
10 premises monitoring station, such as a monitoring company central station, fire station, or police station. In one embodiment, communications link 141 is a telephone line. In another embodiment, communications link 141 is an ISDN (Integrated-Services-Digital Network) line. In another embodiment, communications link 141 uses wireless communications. In other embodiments, any appropriate
15 communications link can be used.

Security devices 116 placed throughout the monitoring area might include door/window open sensors; glass-break sensors, motion detectors, temperature sensors, smoke sensors, infrared sensors, shock sensors, and the like. When security device 116 senses its respective event, the sensor sends a sensor event to control
20 panel 114. In one embodiment, security devices 116 are hardwired to control panel 114. In another embodiment, selected ones or all of the security devices are wireless, in which case the wireless security device includes a wireless transmitter, and control panel 114 includes a wireless receiver.

Security system 112 also can include input devices 120 for user
25 communication with control panel 114. Input devices 120 are shown mounted within control panel 114, but in other embodiments, input devices 120 are packaged separately. Input devices 120 can be hardwired to control panel 114 or wireless. In

some embodiments, the wireless input device can take the form of a portable, wireless unit such as a portable keypad or keychain fob. In other embodiments, input devices 120 are mounted on a wall. An authorized user enters information into the input device to access the control panel. In particular, the user can selectively arm and disarm the security system by entering appropriate information. Also, the user can obtain system status information using the input device, which may provide visual or audible feedback.

In one embodiment, control panel 114 receives alternating electric current via A/C plug 196.

Fig. 2 depicts a block diagram showing additional detail for selected components of the security system of Fig. 1. Control panel 114 is shown receiving signals from sensors 116 and input device 120. Control panel 114 is also shown sending and receiving signals to and from phone interface device 140. Phone interface device 140 is connected via RJ31X jack 284 at phone line demarcation point 285 to a telephone network, which enables phone interface device 140 to transmit and receives signals to and from monitoring station 290. RJ31X jack 284 is a telephone jack that connects alarm equipment to a telephone line. In other embodiments, any appropriate jack can be used. Phone interface device 140 is also connected to facility phone network 295, which is the network of telephones in facility 100.

Control panel 114 contains controller 210, which is coupled to display 220, transmitter 225, and receiver 235. Receiver 235 receives wireless signals containing sensor events and control information from sensors 116 and input device 120. Input devices 120 are shown mounted within control panel 114, but in other embodiments, input devices 120 are packaged separately. Input devices 120 can be hardwired to control panel 114 or wireless. In one embodiment receiver 235 receives RF (radio

frequency) signals. In another embodiment, some or all of sensors 116 and input device 120 are hardwired to control panel 114. Receiver 235 provides the received sense events and to controller 210.

Controller 210 further processes the received information and derives system condition and control information from sense events and other settings and programming information. When appropriate, controller 210 transmits information to siren 125 to cause siren 125 to emit an audio alarm or entry delay beeps for prompting the user to disarm the system. Controller 210 also transmits information to and receives information from phone-interface device 140 via transmitter 225 and receiver 235, as further described below with reference to Figs. 3-5, 7A, and 8B. Controller 210 further causes display 220 to display status information to the user. In one embodiment, transmitter 225 transmits RF signals.

Although input device 120 and siren 125 are shown enclosed within control panel 114, in another embodiment either or both are packaged separately from control panel 114.

In one embodiment, control panel 114 receives alternating electric current via A/C plug 196.

Phone-interface device 140 includes controller 250 coupled to receiver 260, transmitter 265, energy storage device 270, memory 275, phone ports 276 and 277, and sensors 278. Receiver 260 receives signals from transmitter 225. Transmitter 265 sends signals to receiver 235. The operation of controller 250 is further described below with reference to Figs. 4, 5, 6A, 6B, 7B, 8A, 9, and 10-20. In one embodiment, memory 275 is volatile memory such as RAM (Random Access Memory). In another embodiment, memory 275 is non-volatile memory such as a diskette in a diskette drive, a hard disk in a hard-disk drive, or a CD-ROM in a CD-ROM drive.

Controller 210 draws energy from energy storage device 270 and distributes it to receiver 260, transmitter 265, memory 275, and phone ports 276 and 277. In another embodiment, energy storage device 270 is connected directly to receiver 260, transmitter 265, memory 275, and phone ports 276 and 277. In one embodiment, energy storage device 270 is a battery. In another embodiment, energy storage device 270 is a capacitor

Phone port 277 connects to phone line demarcation point 285. Phone port 277 operates to seize the telephone line, dial, and receive electrical energy through the telephone line, as further described below with reference to Figs. 3-8B and 10-20. Phone port 277 further senses information about the telephone line and relays it to controller 250, which transmits it to control panel 114 via transmitter 265. Examples of this sense information includes dial tone/cadence, ring/cadence, line cut, line voltage, line current, caller id, and touch tone signals. Telephone signals pass between controller 250 and monitoring station 290 through phone port 277.

Phone port 276 connects to facility phone network 295. Telephone signals also pass from phone port 276 to facility phone network 295.

Sensors 278 sense trouble conditions in phone-interface device 140 and report them to controller 250, which transmits data about the trouble conditions to control panel 114 via transmitter 140. Examples of trouble conditions include removal of phone port 277 from the phone line, removal of the cover of phone-interface device 140, removal of phone-interface device 140 from its mounting, and low battery or power-supply trouble.

In one embodiment, controller 210 and controller 250 carry out their functions using hardware components, such as logic gates or programmable logic devices. In another embodiment, one or both of controller 210 and 250 are implemented using a computer processor that executes instructions contained in

memory. The instructions defining the functions of this embodiment can be delivered to controller 210 and/or controller 250 via a variety of signal-bearing media, which include, but are not limited to:

(1) information permanently stored on non-writeable storage media (e.g., read only memory devices within a computer such as CD-ROM disks) readable by an unillustrated CD-ROM drive;

(2) alterable information stored on writeable storage media (e.g., floppy disks within a diskette drive, tape drive, or hard-disk drive); or

(3) information conveyed to controller 210 and/or controller 250 by a communications media, such as through a computer or telephone network including wireless communications.

Such signal-bearing media, when carrying computer-readable instructions that direct the functions of the present invention, represent embodiments of the present invention.

The configuration depicted in Fig. 2 is but one possible implementation of the components depicted in Fig. 1, and an embodiment of the invention can apply to any hardware configuration that provides a wireless telephone interface device.

Fig. 3 illustrates a flowchart that describes a method at control panel 114 for receiving and processing events, according to an embodiment of the invention.

Control begins at block 300. Control then continues to block 305 where controller 210 receives an event from input device 120 or receiver 235. Control then continues to block 310 where controller 210 determines whether the event previously received is a door opened and entry delay event. If a door was opened, then an authorized user needs entry delay time to disarm the security system, so if the determination at block 310 is true, then control continues to block 315 where controller 210 sends a

provisional alarm report to phone-interface device 140. Control then returns to block 305, as previously described above.

5 If the determination at block 310 is false, then control continues to block 320 where controller 210 determines whether the event previously received is a sensor event from one of sensors 116 via receiver 235. If the determination at block 320 is true, then control continues to block 325 where controller 210 sends an alarm report to phone-interface device 140. Control then returns to block 305, as previously described above.

10 If the determination at block 320 is false, then control continues to block 330 where controller 210 determines whether the event previously received is a disarm event. A disarm event occurs as a result of a user entering a command to disarm the security system via input device 120. If the determination at block 330 is true, then control continues to block 335 where controller 210 sends a disarm report to phone-interface device 140. Control then returns to block 305, as previously described above.

15 If the determination at block 330 is false, then control continues to block 340 where controller 210 processes other events.

20 Fig. 4 illustrates a flowchart that describes a method at phone-interface device 140 for receiving and processing events, according to an embodiment of the invention. Control begins at block 400. Control then continues to block 405 where phone-interface device 140 receives an event from control panel 114 or an event internal to phone-interface device 140.

25 Control then continues to block 410 where controller 250 determines whether the event previously received is a provisional alarm report from control panel 114. If the determination at block 410 is true, then control continues to block 415 where

controller 250 sets a timer to a period of time. In one embodiment, the timer is an unillustrated hardware timer in phone-interface device 140. In another embodiment the timer is a software timer. Control then returns to block 405, as previously described above.

5 If the determination at block 410 is false, then control continues to block 420 where controller 250 determines whether the event previously received is a timer expiration event. If the determination at block 420 is true, then a period of time has elapsed since the last provisional alarm without receiving a disarm report from control panel 114, so an alarm needs to be communicated to monitoring station 290.

10 Control then continues to block 425 where controller 250 seizes the telephone line. Control then continues to block 430 where controller 250 sends an alarm report to monitoring station 290 via the telephone line. Control then continues to block 435 where controller 250 determines whether the alarm call at block 430 was successful. If the determination at block 435 is true, then control returns to block 405, as

15 previously described above. If the determination at block 435 is false, then control continues to block 440 where controller 250 sends the alarm to monitoring station 290 via a wireless telephone. Control then returns to block 405, as previously described above.

20 If the determination at block 420 is false, then control continues to block 445 where controller 250 determines whether the event previously received is an alarm event. If the determination at block 445 is true, then control continues to block 425, as previously described above.

25 If the determination at block 445 is false, then control continues to block 460 where controller 250 determines whether the event previously received is a disarm event from control panel 114. If the determination at block 460 is true, then a disarm report has been received, which cancels the previous provisional alarm report, so

there is no need to send an alarm to monitoring station 290. Thus, control then continues to block 465 where controller 250 cancels the timer if it was previously set. Control then returns to block 405, as previously described above.

5 If the determination at block 460 is false, then control continues to block 470 where controller 250 processes other events. Control then returns to block 405, as previously described above.

Fig. 5 illustrates a flowchart that describes a method at phone-interface device 140 for transferring data between control panel 114 and monitoring station 290, according to an embodiment of the invention. Control begins at block 500.
10 Control then continues to block 505 where phone-interface device 140 receives data. In one embodiment, the data received is configuration data, which can include an account number. The data received can be either from monitoring station 290 or from control panel 114.

15 Control then continues to block 510 where controller 250 determines whether the received data was from monitoring station 290. If the determination at block 510 is true, control then continues to block 512 where controller 250 optionally determines using caller id whether the calling originates from an authorized monitoring station. If the determination at block 512 is false, then control continues to block 514 where controller 250 returns an error to the caller.

20 If the determination at block 512 is true, then control continues to block 515 where controller 250 determines whether the link between phone-interface device 140 and control panel 114 is fast enough to keep up with the data transfer between monitoring station 290 and phone interface device 140. If the determination at block 515 is true, then control continues to block 520 where controller 250 transfers the
25 data to control panel 114 via transmitter 265 as the data is received from monitoring

station 290 in real time. Control then returns to block 505, as previously described above.

If the determination at block 515 is false, then the link between phone-interface device 140 and control panel 114 is not fast enough to keep up with the data transfer between monitoring station 290 and phone interface device 140, so control continues to block 525 where controller 250 saves the data in memory 275. Once the data transfer between monitoring station 290 and phone-interface device 140 is complete, control continues to block 530 where controller 250 hangs up the telephone. Control then continues to block 540 where controller 250 dribbles the saved data to control panel 114 via transmitter 265 at a data rate that the link between control panel 114 and phone-interface device 114 can handle. Once the data transfer is complete, control continues to block 545 where phone-interface device 140 recalls monitoring station 290 to report success or failure of the data transfer. Control then returns to block 505, as previously described above.

If the determination at block 510 is false, then the received data is from control panel 114, so control continues to block 560 where controller 250 determines whether the link between phone-interface device 140 and control panel 114 is fast enough to keep up with the data transfer between monitoring station 290 and phone-interface device 140. If the determination at block 560 is true, then control continues to block 565 where controller 250 transfers the data to monitoring station 290 as the data is received from control panel 114 in real time. Control then returns to block 505, as previously described above.

If the determination at block 560 is false, then the link between phone-interface device 140 and control panel 114 is not fast enough to keep up with the data transfer between monitoring station 290 and phone interface device 140, so control continues to block 570 where controller 250 dribbles the data in memory 275. Once

the data transfer between control panel 114 and phone-interface device 140 is complete, control continues to block 575 where controller 250 calls monitoring station 290. Control then continues to block 580 where controller 250 dumps the data to monitoring station 290. In another embodiment, controller 250 converts
5 sequences of DTMF tones from control panel 114 into a command and sends the command to monitoring station 290 instead of sending DTMF tones. Once the data transfer is complete, control returns to block 505, as previously described above.

Fig. 6A illustrates a flowchart that describes a method at phone interface device 140 for charging energy storage device 270 from a phone line, according to an
10 embodiment of the invention. Control begins at block 600. Control then continues to block 610 where controller 250 determines whether energy storage device 270 has low electrical power. If the determination at block 610 is false, then control returns to block 610, as previously described above.

If the determination at block 610 is true, then control continues to block 620
15 where controller 250 places a call to monitoring station 290. In another embodiment, instead of placing a call to monitoring station 290, controller 250 sends a message to control panel 114 using transmitter 265, and control panel 114 determines the appropriate next action. Control then continues to block 630 where controller
20 charges energy storage device 270 from the telephone line in various states, such as ringing, while checking the line for proper voltages or currents, while dialing, during a connected call, or after the off-site call party has hung up. Controller 250 adjusts its electrical interface to the phone line so that the entire facility phone system presents the proper current and voltage profile to the outside phone line. That is,
25 controller 250 draws the leftover energy that is available beyond what the facility phone system needs, per telephone company regulations. Control then continues to block 640 where controller 250 hangs up the telephone. Control then returns to block 610, as previously described above.

Fig. 6B illustrates a flowchart that describes a method at phone-interface device 140 for charging energy storage device 270 from a phone line, according to an embodiment of the invention. Control begins at block 650. Control then continues to block 655 where controller 250 determines whether any of the phones in facility 100 are off-hook. If the determination at block 655 is false, control then returns to block 655, as previously described above. In other embodiment, the logic of block 655 is not used, and instead control continues directly from block 650 to block 665, as further described below.

10 If the determination at block 655 is true, then control continues to block 665 where controller 250 draws energy from the phone line in various states, such as ringing, while checking the line for proper voltages or currents, while dialing, during a connected call, and after an off-site call party has hung up. Controller 250 adjusts its electrical interface to the phone line so that the entire facility phone system presents the proper current and voltage profile to the outside phone line. That is, 15 controller 250 draws the leftover energy that is available beyond what the facility phone(s) need, but yet within regulatory allowances.

Figs. 7A and 7B illustrate an embodiment for defeating an intruder who breaks into a facility and disables the control panel prior to the control panel reporting the system condition because of the entry delay previously described 20 above. Figs. 8A and 8B illustrate another embodiment for defeating the intruder.

Fig. 7A illustrates a flowchart that describes a method at control panel 114 for sending a status message to phone-interface device 140, according to an embodiment of the invention. Control begins at block 700. Control then continues to block 710 where controller 210 sends a status message to phone-interface device 25 140 via transmitter 225. Control then continues to block 720 where controller 210

waits for a period of time. Control then returns to block 710, as previously described above.

Fig. 7B illustrates a flowchart that describes a method at phone-interface device 140 for detecting when control panel 114 has an error condition. Control begins at block 750. Control then continues to block 755 where controller 250 waits for a period of time. Control then continues to block 760 where controller 250 determines whether a status message has been received from control panel 114 via receiver 260. If the determination at block 760 is true, then control continues to block 765 where controller 250 determines whether the status message contains information that needs to be communicated to the user. If the determination at block 765 is true, then control continues to block 767 where controller notifies the user of the status. In one embodiment, controller 250 dials one of the facility phones to notify the user. In another embodiment, controller 250 pages the user. In still another embodiment, controller 250 calls an off-premises phone. If the determination at block 765 is false, then control returns to block 755, as previously described above.

If the determination at block 760 is false, then control continues to block 765 where controller 250 determines whether to retry by waiting further. If the determination at block 765 is true, then control returns to block 755 as previously described above. If the determination at block 765 is false, then control continues to block 770 where controller 250 sends an error message to monitoring station 290 indicating that control panel 114 is inoperative. Control then continues to block 799 where the function ends.

Fig. 8A illustrates a flowchart that describes a method at phone-interface device 140 for sending a status message to control panel 114, according to an embodiment of the invention. Control begins at block 800. Control then continues

to block 810 where controller 250 sends a status message to control panel 114. Control then continues to block 820 where controller 250 waits for a period of time. Control then returns to block 810, as previously described above.

Fig. 8B illustrates a flowchart that describes a method at control panel 114 for detecting when phone-interface device 140 has an error condition. Control begins at block 850. Control then continues to block 855 where controller 210 waits for a period of time. Control then continues to block 860 where controller 210 determines whether a status message has been received from phone-interface device 140. If the determination at block 860 is true, then control returns to block 855, as previously described above. If the determination at block 860 is false, then control continues to block 865 where controller 210 displays an error message on display 220, indicating that phone-interface device 140 is inoperative. Control then continues to block 899 where the function returns.

Fig. 9 illustrates a flowchart that describes a method at phone-interface device 140 for receiving telephone calls, according to an embodiment of the invention. Control begins at block 900. Control then continues to block 905 where controller 250 senses and determines the ring pattern of an incoming call. Control then continues to block 910 where controller 250 determines whether the call is intended for control panel 114 based on the ring pattern. If the determination at block 910 is false, then the call is not intended from the control panel, so control continues to block 999 where the function returns.

If the determination at block 910 is true, then control continues to block 930 where controller 250 disconnects the phones within facility phone network 295. Control then continues to block 935 where controller 250 answers the telephone call. Control then continues to block 940 where controller 250 analyzes the information transmitted in the telephone signal and sends the DTMF (Dual Tone Multi-

Frequency, also known as “touch-tone”) tones into codes and transmits the codes to control panel 114 via transmitter 265. In another embodiment, controller 250 translates the DTMF codes into control panel commands and transmits the control panel commands to control panel 114 via transmitter 265. Control then continues to block 999 where the function returns.

Fig. 10 is a flowchart of the RF main routine of controller 250 in phone-interface device 140. Control begins at block 1005. Control then continues to block 1010 where controller 250 determines whether the provisional timer has expired. If the determination at block 1010 is true, then control continues to block 1015 where controller 250 moves the provisional alarms to the report buffer. Control then continues to block 1020 where controller 250 starts the delayed alarms, as further described below with reference to Fig. 13 at entry block 1305. Referring again to Fig. 10, control then continues to block 1099, which returns to block 1005.

If the determination at block 1010 is false, then control continues to block 1025 where controller 250 determines whether it has received an RF command. If the determination at block 1025 is true, then control continues to block 1030, where controller 250 does the RF command, as further described below with reference to Figs. 11-19. Control then continues to block 1099, as previously described above.

If the determination at block 1025 is false, then control continues to block 1035 where controller 250 determines whether 5 pings have been missed. If the determination at block 1035 is true, then control continues to block 1040 where controller 250 tries to resync. Control then continues to block 1050 where controller 250 determines whether it has the panel. If the determination at block 1050 is true, the control continues to block 1099, which returns to block 1005, as previously described above.

If the determination at block 1050 is false, then control continues to block 1055 where controller 250 determines whether the resync tries are done. If the determination at block 1055 is false, then control returns to block 1040, as previously described above.

5 If the determination at block 1055 is true, then control continues to block 1060 where controller 250 determines whether control panel 114 is armed. If the determination at block 1060 is true, the control continues to block 1065 where controller 250 puts the panel failure alarm in the buffer. Control then continues to block 1075 where delayed alarms are started, as described below with reference to
10 Fig. 13 at entry block 1305.

If the determination at block 1060 is false, then control continues to block 1070 where controller 250 puts panel failure trouble in the buffer. Control then continues to block 1075, as previously described above.

15 Fig. 11 is a flowchart of the Provisional Alarm routine of controller 250 in phone-interface device 140. Control begins at block 1100. Control then continues to block 1110 where controller 250 determines whether the provisional timer is on. If the determination at block 1110 is false, then control continues to block 1120 where controller 250 starts the provisional timer. Control then continues to block 1130 where controller 250 buffers the provisional alarm. Control then continues to block
20 1140 where controller 250 returns to the RF Main routine, as previously described above with reference to Fig. 10.

Referring again to Fig. 11, if the determination at block 1110 is true, then control continues directly from block 1110 to block 1130, as previously described above.

Fig. 12 is a flowchart of the Clear Provisional Alarm routine of controller 250 in phone-interface device 140.. Control begins at block 1200. Control then continues to block 1210 where controller 250 determines if the provisional timer is on. If the determination at block 1210 is true, then control continues to block 1220
5 where controller 250 stops the provisional timer. Control then continues to block 1230 where controller 250 clears the provisional alarms. Control then continues to block 1240 where controller 250 returns to the RF Main routine, as previously described above with reference to Fig. 10.

Referring again to Fig. 12, if the determination at block 1210 is false, then
10 control continues directly to block 1240, as previously described above.

Fig. 13 is a flowchart of the Start Delayed Alarms and Delayed Alarm routines of controller 250 in phone-interface device 140.. Control begins at block 1300 for the Delayed Alarm routine and at block 1305 for the Start Delayed Alarms routine. From block 1300, control continues to block 1310 where controller 250
15 buffers the alarm. Control then continues to block 1320 where controller 250 determines whether an alarm is pending. If the determination at block 1320 is false, then control continues to block 1330 where controller 250 determines whether the dialer timer is on. If the determination at block 1330 is false, then control continues to block 1340 where controller 250 starts the dialer timer. Control then continues to
20 block 1350 where controller 250 sets alarm pending. Control then continues to block 1360 where controller 250 returns to the RF Main routine, as previously described above with reference to Fig. 10.

Referring again to Fig. 13, if the determination at block 1330 is true, then control continues directly from block 1330 to block 1360, as previously described
25 above. If the determination at block 1320 is true, then control continues directly from block 1320 to block 1360, as previously described above.

When the routine is entered at block 1305, control continues directly from block 1305 to block 1320, as previously described above.

Fig. 14 is a flowchart of the Immediate Alarm and Start Immediate Alarms routines of controller 250 in phone-interface device 140. Control begins at block 1400 for the Immediate Alarm routine and at block 1405 for the Start Immediate Alarms routine. From block 1400, control continues to block 1410 where controller 250 buffers the alarm. Control then continues to block 1420 where controller 250 determines whether an alarm is pending. If the determination at block 1420 is false, then control continues to block 1430 where controller 250 determines whether the dialer timer is on. If the determination at block 1430 is true, then control continues to block 1440 where controller 250 stops the dialer timer. Control then continues to block 1450 where controller 250 sets alarm pending. Control then continues to block 1460 where controller 250 sets report pending. Control then continues to block 1470 where controller 250 sets a flag to do the report. Control then continues to block 1480 where controller 250 returns to the RF Main routine, as previously described above with reference to Fig. 10.

Referring again to Fig. 14, if the determination at block 1430 is false, then control continues directly from block 1430 to block 1460, as previously described above. If the determination at block 1420 is true, then control continues directly from block 1420 to block 1460, as previously described above.

When the routine is entered at block 1405, control continues directly from block 1405 to block 1420, as previously described above.

Fig. 15 is a flowchart of the Cancel Alarm routine of controller 250 in phone-interface device 140. Control begins at block 1500. Control then continues to block 1510 where controller 250 determines whether an alarm is pending. If the determination at block 1510 is true, then control continues to block 1520 where

controller 250 determines whether the dialer timer is on. If the determination at block 1520 is true, the control continues to block 1530 where controller 250 stops the dialer timer. Control then continues to block 1540 where controller 250 clears alarm pending. Control then continues to block 1550 where controller 250 clears the report buffer. Control then continues to block 1560 where controller 250 returns to the RF Main routine, as previously describe above with reference to Fig. 10.

10 If the determination at block 1520 is false, then control continues to block 1570 where controller 250 buffers a cancel report. Control then continues to block 1580 where controller 250 sets report pending. Control then continues to block 1590 where controller 250 sets a flag to do the report. Control then continues to block 1560, as previously described above.

If the determination at block 1510 is false, then control continues directly from block 1510 to block 1570, as previously described above.

15 Fig. 16 is a flowchart of the Expire Provisional Timer routine of controller 250 in phone-interface device 140. Control begins at block 1600. Control then continues to block 1610 where controller 250 determines whether the provisional timer is on. If the determination at block 1610 is true, then control continues to block 1620 where controller 250 stops the provisional timer. Control then continues to block 1630 where controller 250 moves provisional alarms to the report buffer. Control then continues to block 1640 where controller 250 starts delayed alarms. Control then continues to block 1650 where controller 250 returns to the RF Main routine, as previously described above with reference to Fig. 10.

25 Referring again to Fig. 16, if the determination at block 1610 is false, then control continues directly from block 1610 to block 1650, as previously described above.

Fig. 17 is a flowchart of the Expire Dialer Timer routine of controller 250 in phone-interface device 140. Control begins at block 1700. Control then continues to block 1710 where controller 250 determines whether the dialer timer is on. If the determination at block 1710 is true, then control continues to block 1720 where
5 controller 250 starts immediate alarms. Control then continues to block 1730 where controller 250 returns to the RF Main routine, as previously described above with reference to Fig. 10.

Referring again to Fig. 17, if the determination at block 1710 is false, then control continues directly from block 1710 to block 1730, as previously described
10 above.

Fig. 18 is a flowchart of the Set Armed State routine of controller 250 in phone-interface device 140. Control begins at block 1800. Control then continues to block 1810 where controller 250 sets the armed flag. Control then continues to block 1820 where controller 250 returns to the RF Main routine, as previously described
15 above with reference to Fig. 10.

Fig. 19 is a flowchart of the Set Disarmed State routine of controller 250 in phone-interface device 140. Control begins at block 1900. Control then continues to block 1910 where controller 250 clears the armed flag. Control then continues to block 1920 where controller 250 returns to the RF Main routine, as previously
20 described above with reference to Fig. 10.

Fig. 20 is a flowchart of the Phone Main routine of controller 250 in phone-interface device 140. Control begins at block 2000. Control then continues to block 2005 where controller 250 determines whether the dialer timer is done. If the determination at block 2005 is true, the control continues to block 2010 where
25 controller 250 stops the dialer timer. Control then continues to block 2015 where

controller 250 sets report pending. Control then continues to block 2020 where controller 250 sets a flag to do the report.

Control then continues to block 2025 where controller 250 seizes the communications link. Control then continues to block 2030 where controller 250
5 takes the phone off hook. Control then continues to block 2035 where controller 250 dials the telephone. Control then continues to block 2040 where controller 250 communications with monitoring station 290. Control then continues to block 2045 where controller 2045 clears alarm pending. Control then continues to block 2050 where controller 250 clears report pending. Control then continues to block 2055
10 where controller 255 returns to block 2000, as previously described above.

If the determination at block 2005 is false, then control continues from block 2005 to block 2057 where controller 250 determines if a report is ready to go out. If the determination at block 2057 is true, then control continues from block 2057 to block 2025, as previously described above.

15 If the determination at block 2057 is false, then control continues from block 2057 to block 2060 where controller 250 determines whether there is a ring pattern match. If the determination at block 2060 is true, then control continues from block 2060 to block 2065 where controller 250 seizes the communications link. Control then continues to block 2070 where controller 250 takes the telephone off hook.
20 Control then continues to block 2075 where controller 250 communicates with the downloader. Control then continues to block 2080 where controller 250 returns to block 2000, as previously described above.

If the determination at block 2060 is false, then control returns to block 2000, as previously described above.

25